Version

G

G

G

目录

1 1
1.1 1
1.2 1
2 3
2.1 3
2.2 3
2.3 3
2.3.1 3
2.4 3
3 4
3.1 4
3.2 4
3.3 JET-5310 5
3.4 JET-5310 6
3.5 JET-5310 6
4 7
4.1 7
4.2 7
5 8
5.1 8
5.2 IO 8
5.3 9
5.4 DCIN1 9
5.5 COM1/2/3/4 10
5.6 11
5.6.1 COM5/6 11
5.6.2 PH1 11
5.6.3 F_PANEL 11
5.6.4 INVT1 11
5.6.5 CPU_FAN1 12
5.6.6 USB 12
5.6.7 PWRBTN2 12
5.6.8 JLVDS1 12
5.6.9 LVDS 12
6 13
6.1 JET-5310 13
6.2 14
6.3 M.2 2242/2280 14
6.4 4G/5G 15
6.5 WIFI 15

7 BIOS 16
7.1 BIOS 16
7.2 BIOS 16
7.2.1 BIOS 16
7.2.2 16
7.3 BIOS 17
7.4 Main 17
7.5 Advanced 18
7.6 Chipset 24
7.7 Security 25
7.8 Boot 26
7.9 Save&Exit 27
8 28
8.1 28
8.2 GPIO 29
8.3 Watch Dog 32
8.3.1 Watch Dog 32
8.3.2 32
9 34
9.1 34

1

1.1

JET-5310 BOX Intel Tiger Lake U
G Hυ
Hυ G G
INTEL TGU i3Hυi5Hυi7 CPU HDMI+DP
3 1G 1 4GHυ5G G LPC
G
WINDOWS LINUX G

1.2

	- JET-5310
	- BOX

2

2.1

2.2

2.3

2.3.1

-
-
-
-
-

2.4


-
-
-
- 50mm 100mm
- (
-
- I/O 0.5V


3

3.1

3.3 JET-5310


˜ 2 , M3 x 5.6 G






3.4 JET-5310

˜ 2 , M3 x 5.6 G



3.5 JET-5310

˜ 2 , M3 x 5.6 G



4

4.1


⚠
G

⚠
G G

⚠
G

G I/O USB G I/O G

4.2


DCIN +12V~36V G	

⚠
G


G

5

5.1



5.2 IO




1. PWR_BTN1
2. AUDIO Hυ
3. RECOVER
4. LAN1/2/3/4 RJ45
5. PWR
6. HDD
7. USER: Battery Low
8. HDMI HDMI
9. DP DP
10. USB2.0 USB2.0 Type-A
11. USB3.0 USB3.2 Gen2 Type-A
12. PWR_BTN2
13. DC_IN DC
14. GPIO 3pin I²C +3pin CANBus 2.0 +8pin GPIO
15. COM1/2/3/4
16. ANT1/2/3/4 WIFI

5.3

		LED	
PWR	PC		DC
			PC
HDD			SATA
			NVME


5.4 DCIN1

5.5 COM1/2/3/4



PIN	RS232	RS422	RS485
1	DCD	422TX-	485-
2	SIN	422TX+	485+
3	SOUT	422RX+	/
4	DTR	422RX-	/
5	GND	/	/
6	DSR	/	/
7	RTS	/	/
8	CTS	/	/
9	RI	/	/

COM1-4 RS232/422/485 BIOS




5.6


5.6.1 COM5/6

	1	NDCD	2	NSIN
	3	NSOUT	4	NDTR
	5	GND	6	NDSR
	7	NRTS	8	NCTS
	9	NRI	10	GND


5.6.2 PH1

	1	GND	2	GP_71
	3	GP_70	4	GP_87
	5	GP_86	6	GP_85
	7	GP_84	8	GP_83
	9	GP_82	10	GPIO_PWR
	11	CAN1H	12	CAN1L
	13	GND	14	I2C0_SCL_S
	15	I2C0_SDA_S		

5.6.3 F_PANEL

	1	VCC3
	2	SATA_SSD_LED#
	3	PCH_SATA_LED_N_R
	4	GND
	5	SATA_LED+

5.6.4 INVT1

	1	GND
	2	PWM_OUT1
	3	BKL_EN
	4	BKL_PWR

5.6.6 USB

	1	GND
	2	USB_P9_DP
	3	USB_P9_DN
	4	VCC5


5.6.8 JLVDS1

5.6.9 LVDS

	1	LCD_VCC	2	LCD_VCC
	3	LCD_VCC	4	GND
	5	GND	6	GND
	7	DATA0N	8	DATA0P
	9	DATA1N	10	DATA1P
	11	DATA2N	12	DATA2P
	13	GND	14	GND
	15	CLK1_RN	16	CLK1_RP
	17	DATA3N	18	DATA3P
	19	DATA4N	20	DATA4P
	21	DATA5N	22	DATA5P
	23	DATA6N	24	DATA6P
	25	GND	26	GND
	27	CLK2_RN	28	CLK2_RP
	29	DATA7N	30	DATA7P


6

6.1 JET-5310



1		2		3	
4		5	M3X5_	6	M3X5_
7		8	6#32X5	9	


6.2



DIMM G

1.
2.
3. DIMM
4. DIMM 30° G


6.3 M.2 2242/2280



M.2 1 M2 M.2 2242/2280 SATA SSD G

1. 30°
2. M.2 2242 M.2 2280 M.2 2242 G


6.4 4G/5G



4G/5G G

4G/5G 30° G

6.5 WIFI




WIFI G

WIFI 30° G

7.3 BIOS

Main		BIOS
Advanced		BIOS
Chipset		
Security		
Boot		
Save & Exit		BIOS

7.4 Main




System Date ( )

, “ , / / ” G

System Time


< >< >< > G

7.5 Advanced



Trusted Computing		
Reduce Power		
CPU Configuration	CPU	
SATA Configuration	SATA	
Power Settings		
Super IO Configuration		
Hardware Monitor		

- Trusted Computing <Enter> G



Security Device Support

G Disabled,Enabled.

SHA256 PCR Bank

SHA256 PCR Bank G Disabled,Enabled.

Pending operation

G None,TPM Clear.

Platform Hierarchy

G Disabled,Enabled.

Storage Hierarchy


G Disabled,Enabled.

Endorsement Hierarchy

G Disabled,Enabled.

Physical Presence Spec Version

- Reduce Power <Enter> G



Reduce Power

G Custom,Disabled,Enabled.


- CPU Conf guration <Enter> G



Turbo Mode

Turbo G Disabled,Enabled.


- SATA Conf guration <Enter> g



SATA Controller

SATA g Disabled,Enabled.

- Power Settings <Enter> g



Power Loss

“ ” g On,O f ,Last State.


LAN Wakeup

G Disabled,Enabled.


RTC Wakeup

G Disabled,Enabled.

- Hardware Monitor <Enter> G



7.7 Security



Administrator Password

1. Administrator Password <Enter> G

2. “ Create New Password ” 3~20

<Enter> “ Confrm Password ” G

“ Invalid Password! ” G

“ Administrator Password ” “ Enter Current Password ”

“ Create New Password ” <Enter> G

BIOS Password

G Setup&Post,Setup.

7.8 Boot



Setup Prompt Timeout

G

Boot NumLock State

NumLock G On,Of.

Full Screen Logo

G Disable,Enable.


USB Mass Storage Driver Suoport

USB G Disable,Enable.

Boot Option #1/2/3/4/5/6/7

1 G NVME,Hard Disk:UEFI OS (P0: NS512GSSD340-I),USB Hard Disk,USB Key,USB CD/DVD,Network,UEFI AP: UEFI: Built-in EFI Shell.

7.9 Save&Exit



Save Changes and Reset

G

Discard Changes and Reset

G

Restore Defaults

G

8

JET-1501 JEC-5310 GPIO&Watch Dog

```
    unsigned charret;

    ret = iopl(3);

    if (ret)

    {

        printf("ret = %d \n", ret);

        printf("errno = %d \n", errno);

        printf("error for iopl \n");

        return 1;

    }

    outb(Data, GpioAddress);

    return 0;

}
```

8.2 GPIO

```
        GPIO1~GPIO8     Super IO
GPIO1 --> SIO GPIO71
GPIO2 --> SIO GPIO70
GPIO3 --> SIO GPIO87
GPIO4 --> SIO GPIO86
GPIO5 --> SIO GPIO85
GPIO6 --> SIO GPIO84
GPIO7 --> SIO GPIO83
GPIO8 --> SIO GPIO82

ITE8786 GPIO          Hט
#define ITE8786_Index_Port      0x2E
#define ITE8786_Data_Port       0x2F
#define GPIO_LDN_DEVICE                 0x07
#define GPIO_BASE_ADDRESS               0xa00
GPIO Group 7
#define GPIO7_INPUT_OUTPUT_REGISTER     0xce
#define GPIO7_DATA_REGISTER             GPIO_BASE_ADDRESS
+ 0x06
GPIO Group 8
#define GPIO8_INPUT_OUTPUT_REGISTER     0xcf
#define GPIO8_DATA_REGISTER             GPIO_BASE_ADDRESS
+ 0x07
```

```
//a.        Super IO      Configuration Mode
IoWrite8(ITE8786_Index_Port, 0x87);
IoWrite8(ITE8786_Index_Port, 0x01);
IoWrite8(ITE8786_Index_Port, 0x55);
IoWrite8(ITE8786_Index_Port, 0x55);

//b.                    GPIO, LDN 7
IoWrite8(ITE8786_Index_Port,0x07);
IoWrite8(ITE8786_Data_Port,GPIO_LDN_DEVICE);

   Super IO GPIO Group 7
//c.        GPIO Group7      70~77         GPI
UINT8 BitOffset;
UINT8 GpioNumber;
//Offset 0xce, bits 0~7                0    GPIO70~77         GPI                  G    //              GPIO
                    GPI     GPO                    GPIO          GPIO72                        GPI
   GPO                GPI        GPO G
for(GpioNumber=0x70; GpioNumber<=0x77; GpioNumber++)
{
    BitOffset = GpioNumber - 0x70;
    IoWrite8(ITE8786_Index_Port,GPIO7_INPUT_OUTPUT_REGISTER);
    Data8 = IoRead8(ITE8786_Data_Port);
    Data8 = Data8&(~(0x1<<BitOffset));
    IoWrite8(ITE8786_Data_Port,Data8);
}

//        GPIO Group7      70~77         GPO                                    //    G Offset 0xce, bits
0~7                1    GPIO70~77         GPO                  G
for(GpioNumber=0x70; GpioNumber<=0x77; GpioNumber++)
{
    BitOffset =GpioNumber - 0x70;
    IoWrite8(ITE8786_Index_Port,GPIO7_INPUT_OUTPUT_REGISTER);
    Data8 = IoRead8(ITE8786_Data_Port);
    Data8 = Data8|(0x1<<BitOffset);
    IoWrite8(ITE8786_Data_Port,Data8);
}

//d.    GPIO       G                  GPO              GPIO              GPI              G
//GPIO7_DATA_REGISTER    bits0~7              GPIO70~77              G          bit              0
          GPIO                    1              G
for(GpioNumber=0x70; GpioNumber<=0x77; GpioNumber++)
{
    BitOffset = GpioNumber - 0x70;
    Data8 = IoRead8(GPIO7_DATA_REGISTER);
    Data8 &=~(0x1<<BitOffset);//        bit        0          GPIO
    //Data8 |= 0x1<<BitOffset; /*        bit          1          GPIO              */
    IoWrite8(GPIO7_DATA_REGISTER,Data8);
}

//e.              GPIO                  GPIO7_DATA_REGISTER    bits0~7
GPIO70~77                G
```

```
For(GpioNumber=0x70; GpioNumber<=0x77; GpioNumber++)
{
    BitOffset = GpioNumber - 0x70;
    Data8 = IoRead8(GPIO7_DATA_REGISTER);
    Data8 = Data8>>BitOffset;
    Data8 = Data8 &0x1;
}
if(Data8&0x1){
        return 1;//      GPIO
    }else{
        return 0;//      GPIO
}

  Super IO GPIO Group8
//c-1.      GPIO Group8    80~87      GPI                                    G
UINT8 BitOffset;
UINT8 GpioNumber;
// IN_OUT_SEL_REG_GP8 bits 0~7              0   GPIO80~87      GPI          //      G
  GPIO                    GPI    GPO              //GPIO        GPIO82
  GPI            GPO            GPI      GPO G
for(GpioNumber=0x80; GpioNumber<=0x87; GpioNumber++)
{
    BitOffset = GpioNumber - 0x80;
    IoWrite8(ITE8786_Index_Port, GPIO8_INPUT_OUTPUT_REGISTER);
    Data8 = IoRead8(ITE8786_Data_Port);
    //GPIO80~87      Data8      Bit0~Bit7      Bit                  GPIO    //          G
    Data8 = Data8&(~(0x1<<BitOffset));
    IoWrite8(ITE8786_Index_Port, GPIO8_INPUT_OUTPUT_REGISTER);

    IoWrite8(ITE8786_Data_Port,Data8);
}

//      GPIO Group8    80~87      GPO                                  //    G IN_OUT_SEL_
REG_GP8 bits 0~7            1   GPIO80~87      GPO      //          G
for(GpioNumber=0x80; GpioNumber<=0x87; GpioNumber++)
{
    BitOffset =GpioNumber - 0x80;
    IoWrite8(ITE8786_Index_Port, GPIO8_INPUT_OUTPUT_REGISTER);
    Data8 = IoRead8(ITE8786_Data_Port);
    //GPIO80~87      Data8      Bit0~Bit7      Bit      1          GPIO    //          G
    Data8 = Data8|(0x1<<BitOffset);
    IoWrite8(ITE8786_Index_Port, GPIO8_INPUT_OUTPUT_REGISTER);
    IoWrite8(ITE8786_Data_Port,Data8);
}

//d-1.    GPIO      G                GPO          GPIO          GPI
          G
// IN_OUT_DATA_REG_GP8   bits0~7          GPIO80~87          G
  bit          0          GPIO                  1          G
for(GpioNumber=0x80; GpioNumber<=0x87; GpioNumber++)
{
    BitOffset = GpioNumber - 0x80;
```

```
    //                          GPIO
    // " IN_OUT_DATA_REG_GP8 "              Data O f set Register      G
    Data8 = IoRead8(GPIO_BASE_ADDRESS + IN_OUT_DATA_REG_GP8);
    Data8 &=~(0x1<<BitO f set); //      bit      0        GPIO
    //Data8 |= 0x1<<BitO f set; /*      bit      1        GPIO              */
    IoWrite8(GPIO_BASE_ADDRESS + IN_OUT_DATA_REG_GP8,Data8);
}

//e-1.          GPIO                IN_OUT_DATA_REG_GP8   bits0~7          GPIO80~87
      G
For(GpioNumber=0x80; GpioNumber<=0x87; GpioNumber++)
{
    BitO f set = GpioNumber - 0x80;
    Data8 = IoRead8(GPIO_BASE_ADDRESS + IN_OUT_DATA_REG_GP8);
    Data8 = Data8>>BitO f set;
    Data8 = Data8 &0x1;
}
if(Data8&0x1){
          return 1; //      GPIO
      }else{
          return 0; //      GPIO
}

//f.       Super IO    Con f guration Mode
IoWrite8(ITE8786_Index_Port, 0x02);
IoWrite8(ITE8786_Index_Port, 0x02); //      Super IO Con f guration Mode      SuperIO
                          ,                Con f guration Mode G
```

8.3 Watch Dog

8.3.1 Watch Dog

```
//b.                    GPIO, LDN 7,      GP10       WDT
IoWrite8(SuperIO_Index_Port, 0x07);
IoWrite8(SuperIO_Data_Port , WDT_LDN_DEVICE);

IoWrite8(SuperIO_Index_Port, 0x25);
IoWrite8(SuperIO_Data_Port , (IoRead8(SuperIO_Data_Port) | 0x01));

IoWrite8(SuperIO_Index_Port, 0xC0);
IoWrite8(SuperIO_Data_Port , (IoRead8(SuperIO_Data_Port) | 0x01));

IoWrite8(SuperIO_Index_Port, 0xC8);
IoWrite8(SuperIO_Data_Port , (IoRead8(SuperIO_Data_Port) | 0x01));

IoWrite8(SuperIO_Index_Port, 0xF1);
IoWrite8(SuperIO_Data_Port , (IoRead8(SuperIO_Data_Port) |0x44));

IoWrite8(SuperIO_Index_Port, 0xF4);
IoWrite8(SuperIO_Data_Port , (IoRead8(SuperIO_Data_Port) |0x08));

//c. Clear WDT
IoWrite8(SuperIO_Index_Port, 0x71);
IoWrite8(SuperIO_Data_Port , ((IoRead8(SuperIO_Data_Port) & ~0x10) | 0x01));

//d.       WDT
IoWrite8(SuperIO_Index_Port, 0x72);
Data8 = IoRead8(SuperIO_Data_Port );
Data8 = (Data8&0xc0)|0xc0; //WDT
// Data8 = (Data8&0x40)|0x40; /*WDT                    */
IoWrite8(SuperIO_Data_Port, Data8 );

 //e.       WDT   WDT          0~255          0      WDT                    0          WDT
                                        G
UINT8 Timer;
IoWrite8(SuperIO_Index_Port,0x73);
IoWrite8(SuperIO_Data_Port,Timer); //          Timer                1    255              G
IoWrite8(SuperIO_Index_Port,0x74);
 IoWrite8(SuperIO_Data_Port,0x00); //          Timer              0x00                    Timer
                G

//f.       WDT
IoWrite8(SuperIO_Index_Port,0x73);
IoWrite8(SuperIO_Data_Por, 0x00);

//g.                    WDT Timer
IoWrite8(SuperIO_Index_Port,0x73);
IoWrite8(SuperIO_Data_Port,Timer); //Timer                    1    255              G

//h.       Super IO     Configuration Mode
IoWrite8(SuperIO_Index_Port, 0x02);
IoWrite8(SuperIO_Index_Port, 0x02);//       Super IO Configuration Mode
//SuperIO                                    ,              Configuration Mode G
```

9

9.1

		/
		1Ꮒ 2Ꮒ 12 m ˃ = ==
	“ ”	
		G
		1Ꮒ 2Ꮒ